

Cisco Catalyst 6500 Series 10 Gigabit Ethernet Modules

Product Overview

The Cisco® Catalyst® 6500 Series offer a variety of 10 Gigabit Ethernet modules to serve different needs in the campus and data center for enterprise, commercial, and service provider customers: 16-port 10 Gigabit Ethernet module, 8-port 10 Gigabit Ethernet module, and 4-port 10 Gigabit Ethernet module. These modules support pluggable optics to support distances up to 80 km over single-mode fiber, 300m over multimode fiber, and 15m over copper.

16-Port 10 Gigabit Ethernet Module

The 16-port 10 Gigabit Ethernet module (Figure 1) provides up to 130 10 Gigabit Ethernet ports in a single Cisco Catalyst 6500 chassis and 260 10 Gigabit Ethernet ports in a virtual switching system (VSS) and is targeted for LAN campus aggregation and data center access, where fanout and port density are very important. It consists of 4 port groups of 4 ports each. Users can operate each port group in either oversubscription mode (2 to 4 ports used per port group) or performance mode (1 port used per port group), allowing maximum flexibility for using some ports for connection to servers in performance mode and some other uplinks to wiring closets in oversubscription mode. When in performance mode, up to four 10 Gigabit Ethernet ports can be used to create a virtual switch link in a VSS.¹ In addition, the 16-port 10 Gigabit Ethernet module has reduced power consumption. It uses half the power per port compared to the 8-port 10 Gigabit Ethernet module, providing substantial power savings to the customer.

Figure 1. Cisco Catalyst 6500 Series 16-Port 10 Gigabit Ethernet Module



8-Port 10 Gigabit Ethernet Module

The 8-port 10 Gigabit Ethernet module (Figure 2) provides up to 66 10 Gigabit Ethernet ports in a single Cisco Catalyst 6500 chassis and 132 10 Gigabit Ethernet ports in a VSS. It supports 64 Gbps of local switching, ideal for deployment in the core or aggregation layer of LAN campus and data centers. All 8 ports can be used to create a virtual switch link in a VSS.

Figure 2. Cisco Catalyst 6500 Series 8-Port 10 Gigabit Ethernet Module



¹ Cisco Catalyst 6500 16-port 10 Gigabit Ethernet module support in a Virtual Switching System is in 12.2(33)SXH2. Virtual Switch Link support on the Cisco Catalyst 6500 16-port 10 Gigabit Ethernet module will come in 12.2(33)SXI

4-Port 10 Gigabit Ethernet Module

The 4-port 10 Gigabit Ethernet module (Figure 3) has no oversubscription and is targeted for deployments where line rate is important. It provides up to 34 10 Gigabit Ethernet ports in a single Cisco Catalyst 6500 chassis and 68 10 Gigabit Ethernet ports in a VSS.

Figure 3. Cisco Catalyst 6500 Series 4-Port 10 Gigabit Ethernet Module



All three modules are interoperable with the Cisco Catalyst 6500 Series Virtual Switching Supervisor Engine 720 with 10 Gigabit Ethernet uplinks and Cisco Catalyst 6500 Series Supervisor Engine 720 and provide 40-Gbps connection to the switch fabric. Building upon the award-winning Cisco Catalyst 6500 Series, these 10 Gigabit Ethernet modules are backward compatible with all existing Cisco Catalyst 6500 line cards and services modules, enabling enterprises and service providers to offer new Layer 2 through 7 services and network capabilities to increase revenue and user productivity without complete equipment upgrades.

The Cisco Catalyst 6500 Series 10 Gigabit Ethernet modules are designed for deployment in the distribution and core of campus and data center for traffic aggregation or for interbuilding, points of presence (POPs), WAN edge, and MAN connections. These modules support IEEE 802.3ad link aggregation and Cisco distributed EtherChannel[®] technology for fault-tolerant connectivity and bandwidth scalability of up to 80 Gbps per EtherChannel connection using any 8 ports in the same chassis. In addition, they support hardware-based multicast replication, quality of service (QoS), access control lists (ACLs), jumbo frames, and low latency to enable secure and predictable performance for bandwidth-intensive applications.

Applications

- **16-port 10 Gigabit Ethernet module:** LAN campus and data center distribution; data center access, where fanout and port density are important
- **8-port 10 Gigabit Ethernet module:** data center core and distribution, LAN campus core and distribution, and service provider
- **4-port 10 Gigabit Ethernet module:** core, interbuilding connections, POPs, WAN edge, and MAN connections, where no oversubscription and medium to low 10 Gigabit Ethernet density is required

For more information, see the 10 Gigabit Ethernet Switching for Enterprises white paper at http://www.cisco.com/en/US/products/hw/switches/ps708/products_white_paper0900aecd802a648b.shtml.

Primary Features and Benefits

Table 1 summarizes primary features and benefits of the Cisco Catalyst 6500 Series 10 Gigabit Ethernet modules.

Table 1. Cisco Catalyst 6500 Series 10 Gigabit Ethernet Modules Primary Features Comparison

Feature	WS-X6704-10GE	WS-X6708-10G-3C WS-X6708-10G-3CXL	WS-X6716-10G-3C WS-X6716-10G-3CXL
Ports	4	8	16
Optics	XENPAK	X2	X2
Switch Fabric Connection	40 Gbps (80 Gbps full duplex)	40 Gbps (80 Gbps full duplex)	40 Gbps (80 Gbps full duplex)
Oversubscription	1:1	2:1	4:1
Forwarding Engine	<ul style="list-style-type: none"> Default: centralized forwarding (CFC) Optional: distributed forwarding with DFC3A, DFC3B, DFC3BXL, DFC3C, or DFC3CXL 	<ul style="list-style-type: none"> WS-X6708-10G-3C: equipped with DFC3C for distributed forwarding, supporting 256K routes WS-X6708-10G-3CXL: equipped with DFC3CXL for distributed forwarding, supporting 1M routes 	<ul style="list-style-type: none"> WS-X6716-10G-3C: equipped with DFC3C for distributed forwarding, supporting 256K routes WS-X6716-10G-3CXL: equipped with DFC3CXL for distributed forwarding, supporting 1M routes
Queues	<ul style="list-style-type: none"> RX: 8q8t TX: 1p7q8t 	<ul style="list-style-type: none"> RX: 8q4t TX: 1p7q4t 	Oversubscription mode: <ul style="list-style-type: none"> RX: 1p7q2t per port TX: 1p7q4t per port group Performance mode: <ul style="list-style-type: none"> RX: 8q4t per port TX: 1p7q4t per port
Queuing Mechanisms	<ul style="list-style-type: none"> Class of service (CoS)-based queue mapping 	<ul style="list-style-type: none"> CoS-based queue mapping Differentiated services code point (DSCP)-based queue mapping 	<ul style="list-style-type: none"> CoS-based queue mapping DSCP-based queue mapping
Scheduler	Deficit Weighted Round Robin (DWRR) Weighted Random Early Detection (WRED)	DWRR WRED Shaped Round Robin (SRR) at egress	Oversubscription mode: <ul style="list-style-type: none"> DWRR WRED Performance mode: <ul style="list-style-type: none"> DWRR WRED SRR at egress
Port Buffers	16 MB per port	200 MB per port	Oversubscription mode: 90 MB per port group Performance mode: 200 MB per port
Hardware-Based Multicast Replication	Ingress and egress ~20G per replication engine 2 replication engines per module	Ingress and egress ~50G per replication engine 2 replication engines per module	Ingress and egress ~50G per replication engine 2 replication engines per module
Jumbo Frame Support for Bridged and Routed Packets	Up to 9216 bytes	Up to 9216 bytes	Up to 9216 bytes
Maximum Port Density per Chassis	34 ports (9-slot chassis)	66 ports (9-slot chassis)	130 ports (9-slot chassis)
Maximum Port Density per VSS	68 ports	132 ports	260 ports

Feature	WS-X6704-10GE	WS-X6708-10G-3C WS-X6708-10G-3CXL	WS-X6716-10G-3C WS-X6716-10G-3CXL
Can Be Used to Form Virtual Switch Link	No	Yes	Performance mode—Yes (supported in a subsequent software release) Oversubscription mode—No
Supervisor Engines Supported	Virtual Switching Supervisor Engine 720-10G or Supervisor Engine 720 with any PFC (chassis will work in lowest common denominator mode)	Virtual Switching Supervisor Engine 720-10G or Supervisor Engine 720 with any PFC (chassis will work in lowest common denominator mode)	Virtual Switching Supervisor Engine 720-10G or Supervisor Engine 720 with any PFC (chassis will work in lowest common denominator mode)
Chassis Supported	<ul style="list-style-type: none"> Any Cisco Catalyst 6500 E-Series chassis, C6509-NEB-A chassis, non-E-Series chassis with Fan Tray 2, or Cisco 7600 Series chassis, 7600-S Series chassis (NEBS compliant: operating temperature up to 55°C) Not supported in Cisco Catalyst 6503 non-E Series chassis 	<ul style="list-style-type: none"> Any Cisco Catalyst 6500 E-Series chassis, including 6503-E, 6504-E, 6506-E, 6509-E chassis, 6509-V-E chassis, and C6509-NEB-A chassis with dual fan tray, or the Cisco 7604 chassis and 7609 chassis with dual fan tray, or 7600-S Series chassis (NEBS compliant: operating temperature up to 55°C) Or <ul style="list-style-type: none"> Non-E-Series chassis with Fan Tray 2, including 6506, 6509, 6513 chassis, and C6509-NEB-A with single fan tray or the Cisco 7606, 7613 chassis and 7609 chassis with single fan tray (non-NEBS compliant: operating temperature up to 40°C) Not supported in Cisco Catalyst 6503 non-E Series chassis 	<ul style="list-style-type: none"> Any Cisco Catalyst 6500 E-Series chassis, including 6503-E, 6504-E, 6506-E, 6509-E chassis, 6509-V-E chassis and C6509-NEB-A chassis with dual fan tray (NEBS compliant: operating temperature up to 55°C) Or <ul style="list-style-type: none"> Non-E-Series chassis with Fan Tray 2, including 6506, 6509, 6513 chassis, and C6509-NEB-A with single fan tray (non-NEBS compliant: operating temperature up to 40°C) Not supported in Cisco Catalyst 6503 non-E Series chassis and 7600 Series chassis
Slot Requirements	Can occupy any slot in any Cisco Catalyst 6503-E, 6504-E, 6506, 6506-E, 6509, 6509-E, 6509-V-E, 6509-NEB-A, Cisco 7604, 7607, 7609, 7600-S Series chassis; can only occupy slots 9 through 13 in a Cisco Catalyst 6513 or Cisco 7613 chassis	Can occupy any slot in any Cisco Catalyst 6503-E, 6504-E, 6506, 6506-E, 6509, 6509-E, 6509-V-E, 6509-NEB-A, Cisco 7604, 7606, 7609, 7600-S Series chassis; can only occupy slots 9 through 13 in a Cisco Catalyst 6513 or Cisco 7613 chassis	Can occupy any slot in any Cisco Catalyst 6503-E, 6504-E, 6506, 6506-E, 6509, 6509-E, 6509-V-E, 6509-NEB-A chassis; can only occupy slots 9 through 13 in a Cisco Catalyst 6513 chassis
Onboard Memory	256 MB default, upgradable to 512 MB or 1 GB	1 GB default	1 GB default

The 8-port and 16-port 10 Gigabit Ethernet line cards support the Cisco 10GBASE-CX4, -SR, -LRM, -LX4, -LR, and -ER X2 modules.

The 4-port line card supports the Cisco 10GBASE-CX4, -SR, -LRM, -LX4, -LR, -ER, -ZR, -DWDM, -WDM-REC, and -LW XENPAK modules.

XENPAK and X2 of the same type (for example, XENPAK SR and X2 SR) can be connected to each other.

Table 2 summarizes pluggable optics supported on the Cisco Catalyst 6500 Series 10 Gigabit Ethernet modules.

Table 2. Pluggable Optics for Cisco Catalyst 6500 Series 10 Gigabit Ethernet Modules

X2 Product ID	XENPAK Product ID	Transceiver Type	Wavelength	IEEE Standard	Maximum Distance/Cable Type ²
X2-10GB-LRM	XENPAK-10GB-LRM	10GBASE-LRM	1310 nm serial	802.3aq	220m over multimode fiber
X2-10GB-SR ⁴	XENPAK-10GB-SR	10GBASE-SR	850 nm serial	802.3ae	<ul style="list-style-type: none"> • 26m over 62.5-micron FDDI grade multimode fiber • 33m over 62.5-micron 200 MHz x km multimode fiber • 66m over 50-micron 400 MHz x km multimode fiber • 82m over 50-micron 500 MHz x km multimode fiber • 300m over 50-micron 2000 MHz x km multimode fiber
X2-10GB-LR ⁴	XENPAK-10GB-LR+	10GBASE-LR	1310 nm serial	802.3ae	10 km over single-mode fiber
X2-10GB-ER ⁴	XENPAK-10GB-ER+	10GBASE-ER	1550 nm serial	802.3ae	40 km over single-mode fiber ³
X2-10GB-LX ⁴	XENPAK-10GB-LX4	10GBASE-LX4	WWDM 1310 nm	802.3ae	<ul style="list-style-type: none"> • 300m over 62.5-micron FDDI grade multimode fiber • 240m over 50-micron 400 MHz x km multimode fiber • 300m over 50-micron 500 MHz x km multimode fiber
X2-10GB-CX ⁴	XENPAK-10GB-CX4	10GBASE-CX4	Copper	802.3ak	15m over 8 pair 100-Ohm InfiniBand cable
ZR X2 not available today	XENPAK-10GB-ZR	10GBASE-ZR	1550 nm serial	–	80 km over single-mode fiber
DWDM X2 not available today	DWDM-XENPAK-xx.yy	DWDM	32 different wavelengths; C band	100 GHz ITU grid	32 wavelengths over single strand of single-mode fiber; 80 km ⁵
RX only WDM X2 not available today	WDM-XENPAK-REC	RX only WDM	1530-1565 nm	–	RX only; no TX; 80 km over single-mode fiber
LW X2 not available	XENPAK-10GB-LW	10GBASE-LW	1310 nm serial	802.3ae	10 km over single-mode fiber

² To calculate the exact distances that your module will support before installation, see optical specifications in the XENPAK and X2 data sheets. The exact distance supported varies according to the number of splices and connectors in a single-mode fiber strand.

- Cisco 10GBASE XENPAK modules data sheet
http://www.cisco.com/en/US/prod/collateral/modules/ps2797/ps5138/product_data_sheet09186a008007cd00_ps5455_Products_Data_Sheet.html
- Cisco 10GBASE X2 modules data sheet
http://www.cisco.com/en/US/products/hw/modules/ps5455/products_data_sheet0900aecd801f92aa.html
- Cisco 10GBASE DWDM XENPAK modules data sheet
http://www.cisco.com/en/US/products/hw/modules/ps5455/products_data_sheet0900aecd801f9333.html

³ According to the IEEE 802.3ae standard, requires 5 dB 1550 nm fixed loss attenuator for <20 km; a 5 dB fixed loss attenuator is available as a spare, part number WS-X6K-5DB-ATT=.

⁴ To meet EMI compliance, version -02 or above of SR, LR, ER, LX4, CX4 X2 optics are required for WS-X6708-10G-3C and WS-X6708-10G-3CXL, and version -02 or above of SR and CX4, version -03 or above of ER, version -04 or above of LR and LX4 X2 optics are required for WS-X6716-10G-3C and WS-X6716-10G-3CXL. This restriction does not apply to LRM. See release notes or external Q&A for more details.

⁵ Any passive mux demux can be used with the DWDM XENPAKs. The ONS 15216 Flexlayer filters are one of the options.

X2 Product ID	XENPAK Product ID	Transceiver Type	Wavelength	IEEE Standard	Maximum Distance/Cable Type ²
today					

Product Specifications

Table 3 gives product specifications of the Cisco Catalyst 6500 Series 10 Gigabit Ethernet modules.

Table 3. Product Specifications

Product	Specifications
Standard Protocols	IEEE 802.1d, IEEE 802.1p, IEEE 802.1q, IEEE 802.1s, IEEE 802.1w, IEEE 802.3x, IEEE 802.3ad, IEEE 802.3ae, IEEE 802.3ak, and IEEE 802.3aq
Physical Specifications	<ul style="list-style-type: none"> • Occupies one slot in the Cisco Catalyst 6500 Series chassis or Cisco 7600 Series chassis • Dimensions (H x W x D): 1.2 x 14.4 x 16 in. (3.0 x 35.6 x 40.6 cm) • Weight: <ul style="list-style-type: none"> ◦ 6708 and 6716: 13 pounds excluding X2s. ¼ pound for each X2. ◦ 6704: 10 pounds excluding XENPAKs and DFCs. 2/3 pound for each XENPAK.
Environmental Conditions	<p>Operating temperature:</p> <ul style="list-style-type: none"> • Agency certified for operation: 32° to 104°F (0° to 40°C) • Design and tested for operation 32° to 130°F (0 to 55 °C) • Storage temperature: -40° to 167°F (-40° to 75°C) • Relative humidity: 10 to 90 percent, noncondensing <p>Operating altitude:</p> <ul style="list-style-type: none"> • Agency certified for operation: -150 to 2000m (-500 to 6500 ft) • Designed and tested for operation -150 to 3000m (-500 to 10000 ft)
Regulatory Compliance	<p>Cisco Catalyst 6500 Series 10 Gigabit Ethernet modules, when installed in a system, comply with the following EMC and safety standards:</p> <p>EMC Standards:</p> <ul style="list-style-type: none"> • FCC Part 15 (CFR 47) Class A • ICES-003 Class A • VCCI Class A • EN55022 Class A • EN55024 • CISPR24 • CISPR 22 Class A • AS/NZS CISPR 22 Class A • ETS 300 386 • KN 22 Class A • EN 50082-1 • EN61000-3-2 • EN61000-3-3 • EN61000-6-1 • CNS13438 Class A • KN6100 -4 Series <p>Safety Standards:</p> <ul style="list-style-type: none"> • UL 60950-1 • CAN/CSA C22.2 No. 60950 • EN 60950-1 • IEC 60950-1 • AS/NZS 60950-1 • IEC 60825 Class 1 • EN 60825 Class 1 • 21CFR 1040
NEBS Criteria Levels	<ul style="list-style-type: none"> • SR-3580 Issue 3, June 2007 (GR-63-CORE, issue 3, GR-1089-CORE, issue 4)
ETSI	<ul style="list-style-type: none"> • ETS 300 019-2-1, Class 1.1 Storage • ETS 300 019-2-2, Class 2.1 and 2.2 Transportation • ETS 300 019-2-3, Class 3.1E Stationary Use

Product	Specifications
Network Management	<ul style="list-style-type: none"> • ETHERLIKE-MIB (RFC 1643) • IF-MIB (RFC 1573) • Bridge MIB (RFC 1493) • CISCO-STACK-MIB • CISCO-VTP-MIB • CISCO-CDP-MIB • RMON MIB (RFC 1757) • CISCO-PAGP-MIB • CISCO-STP-EXTENSIONS-MIB • CISCO-VLAN-BRIDGE-MIB • CISCO-VLAN-MEMBERSHIP-MIB • ENTITY-MIB (RFC 2037) • HC-RMON • RFC1213-MIB (MIB-II) • SMON-MIB
Power Requirements	<ul style="list-style-type: none"> • WS-X6716-10G-3C: 457.8W (10.9A @ 42V) • WS-X6716-10G-3CXL: 487.2W (11.6A @ 42V) • WS-X6708-10G-3C: 444.36W (10.58A @ 42v) • WS-X6708-10G-3CXL: 473.76w (11.28A @ 42V) • WS-X6704-10GE with DFC3CXL: 362.46W (8.63A @ 42V) • WS-X6704-10GE with DFC3C: 333.06W (7.93A @ 42V) • WS-X6704-10GE with DFC3BXL: 402.36W (9.58A @ 42V) • WS-X6704-10GE with DFC3B: 377.16W (8.98A @ 42V) • WS-X6704-10GE with DFC3A: 389.76W (9.28A @ 42V) • WS-X6704-10GE with CFC: 295.26W (7.03A @ 42V) <p>Go to http://www.cisco.com/go/powercalculator for easy power consumption calculation.</p>
Indicators	<ul style="list-style-type: none"> • Status: green (operational); red (faulty); orange (module booting) • Link: green (port enabled and connected); orange (port disabled); off (port enabled and not connected)

Ordering Information

Table 4 gives ordering information.

Table 4. Product Numbers for Ordering

Product ID	Product Description
10 Gigabit Ethernet Modules	
WS-X6716-10G-3C	Cisco Catalyst 6500 16-Port 10 Gigabit Ethernet Module with DFC3C, requires X2
WS-X6716-10G-3CXL	Cisco Catalyst 6500 16-Port 10 Gigabit Ethernet Module with DFC3CXL, requires X2
WS-X6708-10G-3C	Cisco Catalyst 6500 8-Port 10 Gigabit Ethernet Module with DFC3C, requires X2
WS-X6708-10G-3CXL	Cisco Catalyst 6500 8-Port 10 Gigabit Ethernet Module with DFC3CXL, requires X2
WS-X6704-10GE	Cisco Catalyst 6500 4-Port 10 Gigabit Ethernet Module, requires XENPAK
Distributed Forwarding Card Upgrades	
WS-F6700-DFC3CXL	Distributed Forwarding Card-3CXL
WS-F6700-DFC3C	Distributed Forwarding Card-3C
WS-F6700-DFC3BXL	Distributed Forwarding Card-3BXL
WS-F6700-DFC3B	Distributed Forwarding Card-3B
WS-F6700-DFC3A	Distributed Forwarding Card-3A
X2 Optics	
X2-10GB-LRM	10GBASE-LRM X2 (multimode fiber)
X2-10GB-SR	10GBASE-SR X2 (multimode fiber)
X2-10GB-LR	10GBASE-LR X2 (single-mode fiber)
X2-10GB-ER	10GBASE-ER X2 (single-mode fiber)

Product ID	Product Description
X2-10GB-LX4	10GBASE-LX4 X2 (multimode fiber)
X2-10GB-CX4	10GBASE-CX4 X2 (copper InfiniBand cable)
XENPAK Optics	
XENPAK-10GB-LRM	10GBASE-LRM XENPAK (multimode fiber)
XENPAK-10GB-SR	10GBASE-SR XENPAK (multimode fiber)
XENPAK-10GB-LR+	10GBASE-LR XENPAK (single-mode fiber)
XENPAK-10GB-ER+	10GBASE-ER XENPAK (single-mode fiber)
XENPAK-10GB-LX4	10GBASE-LX4 XENPAK (multimode fiber)
XENPAK-10GB-CX4	10GBASE-CX4 XENPAK (copper InfiniBand cable)
XENPAK-10GB-ZR	10GBASE-ZR XENPAK (single-mode fiber)
DWDM-XENPAK-xx.yy	DWDM XENPAK, where xx.yy ranges from 30.33 to 60.61 (single-mode fiber)
WDM-XENPAK-REC	RX only XENPAK (single-mode fiber)
XENPAK-10GB-LW	10GBASE-LW XENPAK (single-mode fiber) (WAN PHY)
Cabling for CX4 Transceivers	
CAB-INF-28G-1=	Cisco 1m CX4 patch cable for XENPAK-10GB-CX4
CAB-INF-28G-5=	Cisco 5m CX4 patch cable for XENPAK-10GB-CX4
CAB-INF-28G-10=	Cisco 10m CX4 patch cable for XENPAK-10GB-CX4
CAB-INF-26G-15=	Cisco 15m CX4 patch cable for XENPAK-10GB-CX4

Note:

16-port 10 Gigabit Ethernet module:

- WS-X6716-10G-3C ships with WS-X6716-10GE and WS-F6700-DFC3C.
- WS-X6716-10G-3CXL ships with WS-X6716-10GE and WS-F6700-DFC3CXL.
- The front panel of these modules is labeled as WS-X6716-10GE.
- Cisco IOS[®] Software commands display WS-X6716-10GE with either WS-F6700-DFC3C or WS-F6700-DFC3CXL.

8-port 10 Gigabit Ethernet module:

- WS-X6708-10G-3C ships with WS-X6708-10GE and WS-F6700-DFC3C.
- WS-X6708-10G-3CXL ships with WS-X6708-10GE and WS-F6700-DFC3CXL.
- The front panel of these modules is labeled as WS-X6708-10GE.
- Cisco IOS Software commands display WS-X6708-10GE with either WS-F6700-DFC3C or WS-F6700-DFC3CXL.

Service and Support

Cisco offers a wide range of services programs to accelerate customer success. These innovative services programs are delivered through a unique combination of people, processes, tools, and partners, resulting in high levels of customer satisfaction. Cisco services help you to protect your network investment, optimize network operations, and prepare the network for new applications to extend network intelligence and the power of your business. For more information about Cisco Services, see [Cisco Technical Support Services](#) or [Cisco Advanced Services](#).

For More Information

For more information about Cisco Catalyst 6500 Series Switches, visit <http://www.cisco.com/en/US/products/hw/switches/ps708/index.html> or contact your local account representative.



Americas Headquarters
 Cisco Systems, Inc.
 170 West Tasman Drive
 San Jose, CA 95134-1706
 USA
www.cisco.com
 Tel: 408 526-4000
 800 553-NETS (6387)
 Fax: 408 527-0883

Asia Pacific Headquarters
 Cisco Systems (USA) Pte. Ltd.
 168 Robinson Road
 #28-01 Capital Tower
 Singapore 068912
www.cisco.com
 Tel: +65 6317 7777
 Fax: +65 6317 7799

Europe Headquarters
 Cisco Systems International BV
 Haarlerbergpark
 Haarlerbergweg 13-19
 1101 CH Amsterdam
 The Netherlands
www-europe.cisco.com
 Tel: +31 0 800 020 0791
 Fax: +31 0 20 357 1100

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.

CCVP, the Cisco logo, and Welcome to the Human Network are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn is a service mark of Cisco Systems, Inc.; and Access Registrar, Aironet, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, IP/TV, IQ Expertise, the IQ logo, IQ Net Readiness Scorecard, iQuick Study, LightStream, Linksys, MeetingPlace, MGX, Networkers, Networking Academy, Network Registrar, PIX, ProConnect, ScriptShare, SMARTnet, StackWise, The Fastest Way to Increase Your Internet Quotient, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0711R)