

Cisco Aironet 1250 Series Access Point



The Cisco® Aironet® 1250 Series is an enterprise-class 802.11n access point designed for challenging RF environments. A dual-band rugged indoor access point, the 1250 Series supports data rates of up to 600 Mbps to provide users with reliable and predictable coverage for high-bandwidth data, voice, and video applications.

RF Excellence

Building on the Cisco Aironet heritage of RF excellence, the 1250 Series delivers industry-leading performance for secure and reliable wireless connections. Enterprise-class silicon and optimized radios deliver a robust [mobility](#) experience using Cisco M-Drive technology, which includes:

- [ClientLink](#) improves reliability and coverage for legacy clients
- [BandSelect](#) improves 5-GHz client connections in mixed client environments
- [VideoStream](#) uses multicast to improve rich-media applications

All of these features ensure the best possible end-user experience on the wireless network.

Cisco also offers the industry's broadest selection of [802.11n antennas](#), delivering optimal coverage for a variety of deployment scenarios.

The Cisco Aironet 1250 Series is a component of the Cisco Unified Wireless Network, which can scale up to 18,000 access points with full Layer 3 mobility across central or remote locations on the enterprise campus, in branch offices, and at remote sites. The Cisco Unified Wireless Network is the industry's most flexible, resilient, and scalable architecture, delivering secure access to mobility services and applications and offering the lowest total cost of ownership and investment protection by integrating seamlessly with the existing wired network.

Power Options

With a Gigabit Ethernet (10/100/1000) interface, the Cisco Aironet 1250 Series offers the flexibility of inline as well as local power options. The Cisco Aironet 1250 Series Access Point can be powered by a Cisco Ethernet switch, a power injector, or a local power supply. The number of radio modules determines which Cisco Ethernet switch can power the Aironet 1250 Series Access Point.



Performance with Investment Protection

- Up to nine times faster than 802.11a/g networks
- Backward-compatible with 802.11a/b/g clients
- M-Drive technology optimizes RF

Flexible Platform

- Versatile RF coverage with external antennas
- Supports both 2.4-GHz and 5-GHz modules

Rugged Metal Housing and Extended Operating Temperature

- Ideal for factories, warehouses, and other industrial environments
- UL 2043 plenum rated for above ceiling installation options or suspended from drop ceilings

Secure Interoperability

- 802.11n compliant
- Intel Connect with Centrino Certified

Simplified Network Management

- Controller-based or standalone deployment options

Secure Connections

- Supports rogue access point detection and denial of service attacks
- Management frame protection detects malicious users and alerts network administrators

Greater Network Capacity

- Dynamic frequency selection 2 (DFS-2) compliant

Powering the Aironet 1250 Series Access Point with 802.3af Power over Ethernet

The Aironet 1250 Series Access Point with one RM1252 radio module installed requires 12.95W, which is within the 802.3af Power over Ethernet (PoE) standard. Any Cisco switch supporting 802.3af may be used to power the Aironet 1250 Series Access Point with one RM1252 radio module installed. This is ideal for businesses that chose to only deploy on a single frequency (2.4 GHz or 5 GHz). A single radio provides optimum performance with approximately 300 Mbps maximum PHY data rate. Customers who deploy dual-band, 802.11n radios and power the 1250 Series using standard 802.3af will have more reliable and predictable coverage than that provided by traditional 802.11a/g networks; however, operation will be limited to a single transmitter per radio with maximum PHY data rates of 150 Mbps instead of 300 Mbps per radio. Customers with a significant investment in 802.11 a/b/g client devices that have low-to-medium bandwidth needs but high-reliability requirements will benefit the most from this type of deployment scenario.

Powering the Aironet 1250 Series Access Point with Cisco Enhanced PoE

Cisco Enhanced PoE was designed for customers who want to install new PoE-enabled technologies that require greater than 15.4W per port to function at full capability, such as wireless technology based on the IEEE 802.11n standard. Cisco Enhanced PoE provides the full power requirements for dual-radio modules and eliminates the need to run an additional cabling drop or insert a separate power injector. Support for Enhanced PoE is currently available on a variety of Cisco Catalyst[®] switching platforms. For more information on Enhanced PoE, visit <http://www.cisco.com/en/US/prod/switches/epoe.html>.

Product Specifications

Table 1 lists the product specifications for Cisco Aironet 1250 Series Access Points.

Table 1. Product Specifications for Cisco Aironet 1250 Series Access Points

Item	Specification
Part Numbers	<p>Access point platform with pre-installed radio modules:</p> <ul style="list-style-type: none"> • AIR-AP1252AG-x-K9 802.11a/g/n 2.4/5-GHz Standalone AP; 6 RP-TNC • AIR-AP1252G-x-K9 802.11g/n 2.4-GHz Standalone AP; 3 RP-TNC • AIR-LAP1252AG-x-K9 802.11a/g/n 2.4/5-GHz Unified AP; 6 RP-TNC • AIR-LAP1252G-x-K9 802.11g/n 2.4-GHz Unified AP; 3 RP-TNC <p>Individual components:</p> <ul style="list-style-type: none"> • AIR-AP1250= Standalone AP Platform (no radio modules); Spare • AIR-LAP1250= Unified AP Platform (no radio modules); Spare • AIR-RM1252A-x-K9= 802.11a/n 5-GHz Radio Module; 3 RP-TNC • AIR-RM1252G-x-K9= 802.11g/n 2.4-GHz Radio Module; 3 RP-TNC • AIR-AP1250MNTGKIT= 1250 Series Ceiling, Wall Mount Bracket kit- Spare <p>Eco-pack:</p> <ul style="list-style-type: none"> • AIR-LAP1252-x-K9-5 Eco-pack 802.11a/g/n 2.4/5 GHz Unified AP-5 qty (A, E, N Reg domains only) • AIR-AP1252-N-K9-5 Eco-pack 802.11a/g/n 2.4/5 GHz Standalone AP-5 qty (N Reg domain only) <p>Customers are responsible for verifying approval for use in their individual countries. To verify approval and to identify the regulatory domain that corresponds to a particular country, please visit http://www.cisco.com/go/aironet/compliance.</p>
Software	<ul style="list-style-type: none"> • Cisco IOS[®] Software Release 12.4(21a)JA or later (Standalone Mode) • Cisco IOS Software Release 12.4(10b)JDD or later (Unified Mode) • Cisco Unified Wireless Network Software Release 7.0 or later.
802.11n Capabilities	<ul style="list-style-type: none"> • 2x3 MIMO with two spatial streams • Maximal Ratio Combining (MRC) • 20-and 40-MHz channels • PHY data rates up to 300 Mbps • Packet aggregation: A-MPDU (Tx/Rx), A-MSDU (Tx/Rx) • 802.11 DFS (Bin 5) • Cyclic Shift Diversity (CSD) support
Data Rates Supported	802.11a: 6, 9, 12, 18, 24, 36, 48, and 54 Mbps

Item	Specification			
	802.11g: 1, 2, 5.5, 6, 9, 11, 12, 18, 24, 36, 48, and 54 Mbps			
	802.11n data rates (2.4 GHz and 5 GHz):			
	MCS Index¹	GI² = 800ns		GI = 400ns
		20-MHz Rate (Mbps)	40-MHz Rate (Mbps)	20-MHz Rate (Mbps) 40-MHz Rate (Mbps)
	0	6.5	13.5	7.2 15
	1	13	27	14.4 30
	2	19.5	40.5	21.7 45
	3	26	54	28.9 60
	4	39	81	43.3 90
	5	52	108	57.8 120
	6	58.5	121.5	65 135
	7	65	135	72.2 150
	8	13	27	14.4 30
	9	26	54	28.9 60
	10	39	81	43.3 90
	11	52	108	57.8 120
	12	78	162	86.7 180
	13	104	216	115.6 240
	14	117	243	130 270
	15	130	270	144.4 300
Frequency Band and 20-MHz Operating Channels	A (A Regulatory Domain): <ul style="list-style-type: none"> 2.412 to 2.462 GHz; 11 channels 5.180 to 5.320 GHz; 8 channels 5.500 to 5.700 GHz; 8 channels (excludes 5.600 to 5.640 GHz) 5.745 to 5.825 GHz; 5 channels C (C Regulatory Domain): <ul style="list-style-type: none"> 2.412 to 2.472 GHz; 13 channels 5.745 to 5.825 GHz; 5 channels E (E Reg Domain): <ul style="list-style-type: none"> 2.412 to 2.472 GHz; 13 channels 5.180 to 5.320 GHz; 8 channels 5.500 to 5.700 GHz; 8 channels I (I Regulatory Domain): <ul style="list-style-type: none"> 2.412 to 2.472 GHz; 13 channels 5.180 to 5.320 GHz; 8 channels 		K (K Regulatory Domain): <ul style="list-style-type: none"> 2.412 to 2.472 GHz; 13 channels 5.180 to 5.320 GHz; 8 channels 5.500 to 5.620 GHz; 7 channels 5.745 to 5.805 GHz; 4 channels N (N Regulatory Domain): <ul style="list-style-type: none"> 2.412 to 2.462 GHz; 11 channels 5.180 to 5.320 GHz; 8 channels 5.745 to 5.825 GHz; 5 channels P (P Regulatory Domain): <ul style="list-style-type: none"> 2.412 to 2.472 GHz; 13 channels 5.180 to 5.320 GHz; 8 channels S (S Regulatory Domain): <ul style="list-style-type: none"> 2.412 to 2.472 GHz; 13 channels 5.180 to 5.320 GHz; 8 channels 5.745 to 5.825 GHz; 5 channels T (T Regulatory Domain): <ul style="list-style-type: none"> 2.412 to 2.462 GHz; 11 channels 5.280 to 5.320 GHz; 3 channels 5.500 to 5.700 GHz; 11 channels 5.745 to 5.825 GHz; 5 channels 	
Note: This varies by regulatory domain. Refer to the product documentation for specific details for each regulatory domain.				
Maximum Number of Non-Overlapping Channels	2.4 GHz <ul style="list-style-type: none"> 802.11b/g: <ul style="list-style-type: none"> 20 MHz: 3 802.11n: <ul style="list-style-type: none"> 20 MHz: 3 		5 GHz <ul style="list-style-type: none"> 802.11a: <ul style="list-style-type: none"> 20 MHz: 21 802.11n: <ul style="list-style-type: none"> 20 MHz: 21 	

¹ MCS Index: The **M**odulation and **C**oding **S**cheme (MCS) index determines the number of spatial streams, the modulation, the coding rate, and data rate values.

² GI: A **G**uard **I**nterval (**GI**) between symbols helps receivers overcome the effects of multipath delays.

Item	Specification			
	◦ 40 MHz: 9			
Note: This varies by regulatory domain. Refer to the product documentation for specific details for each regulatory domain.				
Receive Sensitivity	802.11b -90 dBm @ 1 Mb/s -89 dBm @ 2 Mb/s -87 dBm @ 5.5 Mb/s -85 dBm @ 11 Mb/s	802.11g -87 dBm @ 6 Mb/s -86 dBm @ 9 Mb/s -83 dBm @ 12 Mb/s -82 dBm @ 18 Mb/s -81 dBm @ 24 Mb/s -80 dBm @ 36 Mb/s -75 dBm @ 48 Mb/s -74 dBm @ 54 Mb/s	802.11a -86 dBm @ 6 Mb/s -85 dBm @ 9 Mb/s -82 dBm @ 12 Mb/s -81 dBm @ 18 Mb/s -80 dBm @ 24 Mb/s -79 dBm @ 36 Mb/s -74 dBm @ 48 Mb/s -73 dBm @ 54 Mb/s	
	2.4-GHz 802.11n (HT20) -86 dBm @ MC0 -85 dBm @ MC1 -84 dBm @ MC2 -83 dBm @ MC3 -80 dBm @ MC4 -75 dBm @ MC5 -74 dBm @ MC6 -73 dBm @ MC7 -86 dBm @ MC8 -85 dBm @ MC9 -84 dBm @ MC10 -83 dBm @ MC11 -80 dBm @ MC12 -75 dBm @ MC13 -74 dBm @ MC14 -73 dBm @ MC15		5-GHz 802.11n (HT20) -85 dBm @ MC0 -84 dBm @ MC1 -83 dBm @ MC2 -82 dBm @ MC3 -79 dBm @ MC4 -74 dBm @ MC5 -73 dBm @ MC6 -72 dBm @ MC7 -85 dBm @ MC8 -84 dBm @ MC9 -83 dBm @ MC10 -82 dBm @ MC11 -79 dBm @ MC12 -74 dBm @ MC13 -73 dBm @ MC14 -72 dBm @ MC15	5-GHz 802.11n (HT40) -85 dBm @ MC0 -84 dBm @ MC1 -83 dBm @ MC2 -79 dBm @ MC3 -76 dBm @ MC4 -71 dBm @ MC5 -70 dBm @ MC6 -69 dBm @ MC7 -85 dBm @ MC8 -84 dBm @ MC9 -83 dBm @ MC10 -79 dBm @ MC11 -76 dBm @ MC12 -71 dBm @ MC13 -70 dBm @ MC14 -69 dBm @ MC15
Maximum Transmit Power	2.4GHz <ul style="list-style-type: none"> • 802.11b <ul style="list-style-type: none"> ◦ 23 dBm with 1 antenna • 802.11g <ul style="list-style-type: none"> ◦ 20 dBm with 1 antenna • 802.11n (HT20) <ul style="list-style-type: none"> ◦ 17 dBm with 1 antenna ◦ 20 dBm with 2 antennas 		5GHz <ul style="list-style-type: none"> • 802.11a <ul style="list-style-type: none"> ◦ 17 dBm with 1 antenna • 802.11n non-HT duplicate (802.11a duplicate) mode <ul style="list-style-type: none"> ◦ 17 dBm with 1 antenna • 802.11n (HT20) <ul style="list-style-type: none"> ◦ 17 dBm with 1 antenna ◦ 20 dBm with 2 antennas • 802.11n (HT40) <ul style="list-style-type: none"> ◦ 17 dBm with 1 antenna ◦ 20 dBm with 2 antennas 	
Note: The maximum power setting will vary by channel and according to individual country regulations. Refer to the product documentation for specific details.				
Available Transmit Power Settings	2.4GHz 23 dBm (200 mW) 20 dBm (100 mW) 17 dBm (50 mW) 14 dBm (25 mW) 11 dBm (12.5 mW) 8 dBm (6.25 mW) 5 dBm (3.13 mW) 2 dBm (1.56 mW) -1 dBm (0.78 mW)		5GHz 20 dBm (100 mW) 17 dBm (50 mW) 14 dBm (25 mW) 11 dBm (12.5 mW) 8 dBm (6.25 mW) 5 dBm (3.13 mW) 2 dBm (1.56 mW) -1 dBm (0.78 mW)	
Note: The maximum power setting will vary by channel and according to individual country regulations. Refer to the product documentation for specific details.				
Antenna Connectors	<ul style="list-style-type: none"> • 2.4-GHz: 3 RP-TNC connectors • 5-GHz: 3 RP-TNC connectors 			
Interfaces	<ul style="list-style-type: none"> • 10/100/1000BASE-T autosensing (RJ-45) 			

Item	Specification		
	<ul style="list-style-type: none"> Management console port (RJ45) 		
Indicators	<ul style="list-style-type: none"> Status LED indicates operating state, association status, error/warning condition, boot sequence, and maintenance status. Ethernet LED indicates activity over the Ethernet, status. Radio LED indicates activity over the radio, status. 		
Modularity	<ul style="list-style-type: none"> Number of radio module slots: 2 Available radio modules 		
	Part Number	Description	Maximum per AP1250 platform
	AIR-RM1252A-x-K9	2.4 802.11a/n-d2.0 5-GHz Radio Module; 3 RP-TNC	1
	AIR-RM1252G-x-K9	802.11g/n-d2.0 2.4-GHz Radio Module; 3 RP-TNC	1
Dimensions (W x L x H)	<ul style="list-style-type: none"> AP (without mounting bracket): 8.12 x 9.52 x 2.35 in. (20.62 x 24.18 x 5.97 cm) AP (with mounting bracket): 8.12 x 9.52 x 2.75 in. (20.62 x 24.18 x 6.99 cm) 		
Weight	<ul style="list-style-type: none"> AP with 2 radios installed: 5.1 lbs (2.31 kg) AP chassis: 2.1 lbs (0.95 kg) 2.4 GHz radio: 1.5 lbs (0.68 kg) 5 GHz radio: 1.5 lbs (0.68 kg) 		
Environmental	<p>Nonoperating (storage) temperature: -40 to 185°F (-40 to 85°C)</p> <p>Operating temperature: -4 to +131°F (-20 to +55°C)</p> <p>Operating humidity: 10 to 90 percent (noncondensing)</p>		
System Memory	<ul style="list-style-type: none"> 64 MB DRAM 32 MB flash 		
Input Power Requirements	<ul style="list-style-type: none"> AP1250: 36 to 57 VDC Power Supply and Power Injector: 100 to 240 VAC; 50 to 60 Hz 		
Powering Options	<ul style="list-style-type: none"> Cisco Catalyst switch port capable of sourcing 20W or greater Cisco AP1250 Power Injector (AIR-PWRINJ4) Cisco AP1250 Local Power Supply (AIR-PWR-SPLY1) 802.3af switch (AP1250 with single radio only) 		
Power Draw	<ul style="list-style-type: none"> AP1250 with two RM1252 radio modules installed: 18.5W AP1250 with one RM1252 radio module installed: 12.95W <p>Note: For a 1250 Series Access Point with two radios, 18.5W is the maximum power required at the access point (powered device). When deployed using PoE, the power drawn from the power sourcing equipment will be higher by some amount dependent on the length of the interconnecting cable. This additional power may be as high as 1.5W, bringing the total system power draw (access point + cabling) to 20W. A similar consideration applies for a 1250 Series Access Point with one radio.</p>		
Warranty	Limited Lifetime Hardware Warranty		

Item	Specification
Compliance	<p>Standards</p> <ul style="list-style-type: none"> • Safety: <ul style="list-style-type: none"> ◦ UL 60950-1 ◦ CAN/CSA-C22.2 No. 60950-1 ◦ UL 2043 ◦ IEC 60950-1 ◦ EN 60950-1 • Radio approvals: <ul style="list-style-type: none"> ◦ FCC Part 15.247, 15.407 ◦ RSS-210 (Canada) ◦ EN 300.328, EN 301.893 (Europe) ◦ ARIB-STD 33 (Japan) ◦ ARIB-STD 66 (Japan) ◦ ARIB-STD T71 (Japan) ◦ AS/NZS 4268.2003 (Australia and New Zealand) ◦ EMI and susceptibility (Class B) ◦ FCC Part 15.107 and 15.109 ◦ ICES-003 (Canada) ◦ VCCI (Japan) ◦ EN 301.489-1 and -17 (Europe) ◦ EN 60601-1-2 EMC requirements for the Medical Directive 93/42/EEC • IEEE Standard <ul style="list-style-type: none"> ◦ IEEE 802.11a/b/g, IEEE 802.11n, IEEE 802.11h, IEEE 802.11d • Security: <ul style="list-style-type: none"> ◦ 802.11i, Wi-Fi Protected Access 2 (WPA2), WPA ◦ 802.1X ◦ Advanced Encryption Standards (AES), Temporal Key Integrity Protocol (TKIP) • EAP Type(s): <ul style="list-style-type: none"> ◦ Extensible Authentication Protocol-Transport Layer Security (EAP-TLS) ◦ EAP-Tunneled TLS (TTLS) or Microsoft Challenge Handshake Authentication Protocol Version 2 (MSCHAPv2) ◦ Protected EAP (PEAP) v0 or EAP-MSCHAPv2 ◦ Extensible Authentication Protocol-Flexible Authentication via Secure Tunneling (EAP-FAST) ◦ PEAPv1 or EAP-Generic Token Card (GTC) ◦ EAP-Subscriber Identity Module (SIM) • Multimedia: <ul style="list-style-type: none"> ◦ Wi-Fi Multimedia (WMM™) • Other: <ul style="list-style-type: none"> ◦ FCC Bulletin OET-65C ◦ RSS-102
Calculated Mean Time Between Failure (MTBF)	380,000 hours

Service and Support

Cisco and Cisco [Wireless LAN](#) Specialized Partners offer a broad portfolio of end-to-end services based on proven methodologies for planning, designing, implementing, operating, and optimizing the performance of your wireless network.

Cisco recommends the following services for the Cisco Aironet 1250 Series Access Points implementation:

Limited Lifetime Hardware Warranty

This Cisco Aironet 1250 Series Access Point comes with a Limited Lifetime Warranty that provides full warranty coverage of the hardware for as long as the original end user continues to own or use the product. The warranty includes 10-day advance hardware replacement and ensures that software media is defect-free for 90 days. For more details, visit: <http://www.cisco.com/go/warranty>

Cisco Wireless LAN 802.11n Readiness Assessment Service

Prevent common challenges and reduce deployment costs by determining the readiness of your wired and wireless infrastructure.

Cisco Wireless LAN 802.11n Migration Service

Simplify the migration to high-performance, next generation 802.11n.

Cisco Wireless LAN Optimization Service

Evolve your 802.11n network to meet ever-changing network demands through planning and assessments, design, performance tuning, and ongoing support for system changes.

For more information about Cisco 802.11n planning and deployment services, visit

<http://www.cisco.com/go/wirelesslanservices>.

For More Information

For more information about the Cisco Aironet 1250 Series, visit <http://www.cisco.com/go/wireless> or contact your local account representative.



Americas Headquarters
Cisco Systems, Inc.
San Jose, CA

Asia Pacific Headquarters
Cisco Systems (USA) Pte. Ltd.
Singapore

Europe Headquarters
Cisco Systems International BV
Amsterdam, The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at www.cisco.com/go/offices.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)